

Adaptive Voice Amplification - tuning table

Dynamic boost - disabled					Nureva® App settings					
Wireless microphones										
Transmitter and receiver system	Mirophone type	Transmitter gain (dB)	Receiver gain (dB)	Computer system volume (%)	Aux-in	Dynamic boost	Microphone ducking	HDL system speaker gain (dB)	USB: Far end gain (dB)	Gate threshold
Shure® QLXD14	Lavalier (cardioid)	6	4	80	Line	Off	On	15	12	170
	Lavalier (supercardioid)	6	4	80	Line	Off	On	15	12	170
	Lavalier (omnidirectional)	0	-2	80	Line	Off	On	15	10	110
	Handheld (SM58)	15	-2	80	Line	Off	On	15	10	50
	Headset (SM35)	6	4	80	Line	Off	On	15	12	36
Shure ULX-D	Lavalier (cardioid)	6	4	80	Line	Off	On	15	12	170
	Lavalier (supercardioid)	6	4	80	Line	Off	On	15	12	170
	Lavalier (omnidirectional)	0	-2	80	Line	Off	On	15	10	110
	Handheld (SM58)	15	-2	80	Line	Off	On	15	10	50
	Headset (SM35)	6	4	80	Line	Off	On	15	12	36
Shure BLX14	Lavalier (cardioid)	11 o'clock	N/A	80	Mic	Off	On	20	12	80
	Lavalier (supercardioid)	11 o'clock	N/A	80	Mic	Off	On	20	12	80
	Lavalier (omnidirectional)	10 o'clock	N/A	80	Mic	Off	On	15	9	93
	Handheld (SM58)	N/A	N/A	80	Mic	Off	On	20	9	64
	Headset (SM35)	11 o'clock	N/A	80	Mic	Off	On	15	8	50
Sennheiser EM-XSW 1	Headset (ME-3)	0	4	80	Mic	Off	On	20	9	64
Wired microphones										
Transmitter and receiver system	Mirophone type	Transmitter gain (dB)	Receiver gain (dB)	Computer system volume (%)	Aux-in	Dynamic boost	Microphone ducking	HDL system speaker gain (dB)	USB: Far end gain (dB)	Gate threshold
Shure	Gooseneck (CVG18D)	N/A	N/A	80	Line	Off	On	15	12	64
		* Set at the mixer								