

PACKAGE CONTENTS


- 1 4.5" Combo Push Button & LED Annunciator
- 1 Alarm Strobe Siren
- 1 Signboard
- 4 Tamperproof screws
- 8 SS FLT HD Screws
- 1 Tamperproof driver



ADC-EB-55A-EM
4.5" Combo Push Button & LED Annunciator



ADC-EB-55A-LS
Alarm Strobe Siren



Signboard

DESCRIPTION

The Emergency kit Series provide more security for high traffic areas that require a visual indicator for an occupied or locked space such as a conference room, restroom or a secure area. It can be surface or flush mounted. When not illuminated, the sign (text and/or graphics) is invisible. When illuminated, the text/graphics are highly visible -even in daylight

APPLICATION

AiBase illuminated Annunciator with sounder is ideal for areas that require a visual and audible indicator with emergency assistance has been requested such as restrooms or hospital rooms. It can be surface or flush mounted. AiBase Illuminated Annunciator is designed to be controlled by electric locks, electric-magnetic locks, electric strikes, automatic doors and low energy operators.

SPECIFICATION

Illuminated Annunciator	
VOLTAGE:	AC/DC 8-24V(Led Annunciator)
CURRENT DRAW:	70-80mA(Led Annunciator)
TEMP RANGE:	-20°C - +60°C
SOUNDER:	Adjustable, 85dB @ 10cm max.
PUSH BUTTON:	Maintained (Push/Pull), N/O & N/C, 5A @ 30 VDC
DIMENSIONS:	4-1/2" H x 4-1/2" W (115mm x 115mm)

Alarm Strobe Siren	
VOLTAGE:	AC/DC 6-15V
CURRENT DRAW:	280mA
SPL:	115dB/1M
GR Weight:	110g
DIMENSIONS:	122*73*43mm

WARNING:

Do NOT apply power to the unit until all wiring



WIRING DIAGRAM

